



# Antenna Datasheet

**Product OC:** YCGO010AA

**Version:** 2.0

**Date:** 2023-08-26

**Status:** Released

**Product Name:** Active GPS L1 & BEIDOU B1 Antenna

**Key Features:**

Frequency Band: 1559–1586 MHz

Dimensions: 18 × 18 × 6.3 mm

Efficiency: Up to 42.5 %

RoHS Compliant

LNA Gain: 18 ±3 dB

# Overview

This Quectel GNSS antenna adopts a diversity of forms to guarantee the most suitable polarization type. Quectel's positioning products support single-band or multi-band operation modes to meet various high-precision positioning requirements of customers' products. Quectel also provides both passive and active antennas to satisfy the customer demand for high gain. Such antenna supports different installation or connection methods such as pin mount, surface mount, magnetic mount, internal cable, and external SMA. Customized connector type and cable length are provided according to requirements.

# Contents

<b>Overview</b> .....	<b>1</b>
<b>Contents</b> .....	<b>2</b>
<b>1 Specification</b> .....	<b>3</b>
1.1. Electrical.....	3
1.2. Mechanical & Environmental .....	4
1.3. Block Diagram (Active Antenna).....	5
1.4. Supported GNSS Frequency Bands.....	6
<b>2 Drawing</b> .....	<b>8</b>
<b>3 Detailed Performance</b> .....	<b>9</b>
3.1. S-Parameter Test .....	9
3.1.1. VSWR.....	9
3.1.2. Return Loss .....	10
3.1.3. GNSS LNA Gain.....	11
3.1.4. Noise Figure .....	12
3.2. Radiation Performance Test.....	13
3.2.1. Efficiency .....	13
3.2.2. Peak Gain.....	14
3.2.3. 3D & 2D Radiation Pattern.....	15
<b>4 Packaging</b> .....	<b>17</b>
<b>Contact Us</b> .....	<b>19</b>
<b>Legal Notices</b> .....	<b>20</b>
<b>Revision History</b> .....	<b>22</b>

# 1 Specification

Test Condition: By 40 mm square ground plane

## 1.1. Electrical

Electrical	
Frequency Range	1559–1586 MHz
Impedance	50 Ω
Polarization	RHCP
Radiation Pattern	Directional


Band Frequency (MHz)	GPS L5 GALILEO E5a BEIDOU B2a-B2I QZSS L5 IRNSS L5	GALILEO E5b BEIDOU B2b	GPS L2 QZSS L2C	GLONASS G2	BEIDOU B3	BEIDOU B1I	GPS L1 GALILEO E1 BEIDOU B1C QZSS L1	GLONASS G1
	1176	1207	1227	1248	1268	1561	1575	1602
VSWR	-	-	-	-	-	1.5	1.4	-
Return Loss (dB)	-	-	-	-	-	-13.8	-15.6	-
Efficiency (%)	-	-	-	-	-	42.5	40.5	-
Peak Gain (dBi)	-	-	-	-	-	1.9	0.6	-

LNA Electrical	
LNA Gain	18 ±3 dB
Noise Figure	≤ 1.5 dB
Output VSWR	< 2.0
Filter Out-of-band Attenuation	32 dB f0 ±100 MHz f0 (1568 MHz)
Working Voltage	2.7–3.3 V
Working Current	8 ±2 mA @ 3 V
Impedance	50 Ω

## 1.2. Mechanical & Environmental

Mechanical	
Antenna Dimensions	18 × 18 × 6.3 mm
Material	PCB + Ceramic
Cable Type & Color & Length	Φ 1.13 & Black & 50 mm
Connector Type	IPEX MHF 1
Mounting Type	Buckle
Weight	Typ. 7.5 g
Environmental	
Operation Temperature	-40 °C to +85 °C
Storage Temperature	-40 °C to +85 °C
RoHS Compliant	Yes


### 1.3. Block Diagram (Active Antenna)



## 1.4. Supported GNSS Frequency Bands


GNSS Frequency Bands (MHz)					
<b>GPS</b>	<b>L1</b> Centre 1575.42 (1565–1586)	<b>L2</b> Centre 1227.6 (1217–1238)	<b>L5</b> Centre 1176.45 (1164–1189)		
	√	-	-		
<b>GLONASS</b>	<b>G1-L10C-L10F</b> Centre 1601 (1595–1606)	<b>G2-L20C-L20F</b> Centre 1248.06 (1241–1255)	<b>G3-L30C</b> Centre 1202.025 (1189–1213)		
	-	-	-		
<b>GALILEO</b>	<b>E1</b> Centre 1575.42 (1563–1588)	<b>E5a</b> Centre 1176.45 (1166–1187)	<b>E5b</b> Centre 1207.14 (1197–1218)	<b>E6</b> Centre 1278.75 (1258–1300)	
	√	-	-	-	
<b>BEIDOU</b>	<b>B1I</b> Centre 1561.098 (1559–1564)	<b>B1C (BeiDou-3)</b> Centre 1575.42 (1559–1592)	<b>B2b</b> Centre 1176.45 (1166–1187)	<b>B2a-B2I</b> Centre 1207.14 (1197–1217)	<b>B3</b> Centre 1268.52 (1258–1279)
	√	√	-	-	-
<b>QZSS</b>	<b>L1</b> Centre 1575.42 (1573–1578)	<b>L2C</b> Centre 1227.6 (1226–1229)	<b>L5</b> Centre 1176.45 (1166–1187)	<b>L6</b> Centre 1278.75 (1257–1300)	
	√	-	-	-	
<b>IRNSS</b>	<b>L5</b> Centre 1176.45 (1164–1189)				
	-				

### GNSS Bands and Constellations






# 2 Drawing



# 3 Detailed Performance

## 3.1. S-Parameter Test


### 3.1.1. VSWR



VSWR

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
VSWR	-	-	-	-	-	1.5	1.4	-


**3.1.2. Return Loss**



**Return Loss (dB)**

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Return Loss (dB)	-	-	-	-	-	-13.8	-15.6	-


**3.1.3. GNSS LNA Gain**



**LNA Gain (dB)**

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
LNA Gain (dB)	-	-	-	-	-	18.2	17.8	-

**3.1.4. Noise Figure**




**Noise Figure (dB)**

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Noise Figure (dB)	-	-	-	-	-	1.4	1.4	-

### 3.2. Radiation Performance Test


#### 3.2.1. Efficiency



**Efficiency (%)**

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Efficiency (%)	-	-	-	-	-	42.5	40.5	-

**3.2.2. Peak Gain**



**Peak Gain (dBi)**


Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
Peak Gain (dBi)	-	-	-	-	-	1.9	0.6	-

### 3.2.3. 3D & 2D Radiation Pattern




- Test Condition: By 40 mm square ground plane
- Test Chamber: GL-S-1









# 4 Packaging

Step	Packaging Picture / 2D Picture	Description
1		<p>Put the product into the pearl cotton tray; (80 pcs per cotton tray) Put the tray in a vacuum bag to vacuum.</p>
2		<p>Put 5 vacuum bags into the carton box; (400 pcs antennas per carton box)</p> <p><u>Carton Box Size:</u> <u>L × W × H = 405 × 293 × 185 mm</u></p>
3		<p>Put a bubble bag on the top of product</p>

4		<p><b>Position for Attaching Labels</b></p> <ul style="list-style-type: none"><li>① Carton Label</li><li>② Quality Label</li></ul>
5		<p><b>Sealing Cartons</b></p> <p>“工” type sealing cartons</p>

# Contact Us

At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

**Quectel Wireless Solutions Co., Ltd.**

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236

Email: [info@quectel.com](mailto:info@quectel.com)

**Or our local offices. For more information, please visit:**

<http://www.quectel.com/support/sales.htm>.

**For technical support, or to report documentation errors, please visit:**

<http://www.quectel.com/support/technical.htm>.

Or email us at: [support@quectel.com](mailto:support@quectel.com).

# Legal Notices

We offer information as a service to you. The provided information is based on your requirements and we make every effort to ensure its quality. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an “as available” basis. We may revise or restate this document from time to time at our sole discretion without any prior notice to you.

## Use and Disclosure Restrictions

### License Agreements

Documents and information provided by us shall be kept confidential, unless specific permission is granted. They shall not be accessed or used for any purpose except as expressly provided herein.

### Copyright

Our and third-party products hereunder may contain copyrighted material. Such copyrighted material shall not be copied, reproduced, distributed, merged, published, translated, or modified without prior written consent. We and the third party have exclusive rights over copyrighted material. No license shall be granted or conveyed under any patents, copyrights, trademarks, or service mark rights. To avoid ambiguities, purchasing in any form cannot be deemed as granting a license other than the normal non-exclusive, royalty-free license to use the material. We reserve the right to take legal action for noncompliance with abovementioned requirements, unauthorized use, or other illegal or malicious use of the material.

### Trademarks

Except as otherwise set forth herein, nothing in this document shall be construed as conferring any rights to use any trademark, trade name or name, abbreviation, or counterfeit product thereof owned by Quectel or any third party in advertising, publicity, or other aspects.

### Third-Party Rights

This document may refer to hardware, software and/or documentation owned by one or more third parties (“third-party materials”). Use of such third-party materials shall be governed by all restrictions and obligations applicable thereto.

We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise maintain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing or usage of trade.

## Privacy Policy

To implement module functionality, certain device data are uploaded to Quectel's or third-party's servers, including carriers, chipset suppliers or customer-designated servers. Quectel, strictly abiding by the relevant laws and regulations, shall retain, use, disclose or otherwise process relevant data for the purpose of performing the service only or as permitted by applicable laws. Before data interaction with third parties, please be informed of their privacy and data security policy.

## Disclaimer

- a) We acknowledge no liability for any injury or damage arising from the reliance upon the information.
- b) We shall bear no liability resulting from any inaccuracies or omissions, or from the use of the information contained herein.
- c) While we have made every effort to ensure that the functions and features under development are free from errors, it is possible that they could contain errors, inaccuracies, and omissions. Unless otherwise provided by valid agreement, we make no warranties of any kind, either implied or express, and exclude all liability for any loss or damage suffered in connection with the use of features and functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage may have been foreseeable.
- d) We are not responsible for the accessibility, safety, accuracy, availability, legality, or completeness of information, advertising, commercial offers, products, services, and materials on third-party websites and third-party resources.

***Copyright © Quectel Wireless Solutions Co., Ltd. 2023. All rights reserved.***

# Revision History

Version	Date	Author	Note
-	2021-05-19	Kenny YIN/ Aria CHU	Creation of the document
1.0	2021-05-19	Kenny YIN/ Aria CHU	First official release
1.1	2021-07-25	Kenny YIN/ Aria CHU	Updated working temperature (Chapter 3).
1.2	2021-11-30	Kenny YIN/ Aria CHU	Updated the product description (Chapter 1).
1.3	2023-06-25	Toby WANG/ Vinnie LIU	Updated the drawing (Chapter 5).
2.0	2023-08-26	Nico PAN/ Lucky FENG/ David LIU/ Aria CHU	Updated all test data in this datasheet.

**QUECTEL**

[www.quectel.com](http://www.quectel.com)

