



Antenna Datasheet

Product OC: YEGT001W1AM

Version: 1.4

Date: 2026-01-12

Status: Released

Product Name: GNSS Terminal Mount Rubber Passive External Antenna

Key Features:

Frequency Band: 1559–1606 MHz

Dimensions: 135 mm × 15.6 mm × 13 mm

Efficiency: Up to 78.2 %

RoHS Compliant

Compatible with FAKRA, TNC and N-Type connectors

Overview

The Quectel YEGT001W1AM is a high-performance GNSS terminal mount external dipole antenna designed for precision navigation and positioning applications. Operating in the 1559–1606 MHz frequency band, it supports GPS L1, GLONASS G1, Galileo E1, and BDS B1I/B1C systems, making it ideal for automotive, industrial tracking, IoT, and telematics solutions where reliable signal reception is critical.

- **Key Features**

- ✓ **Exceptional Efficiency:** Achieves up to 78.2% efficiency in free-space conditions, ensuring robust signal capture even in challenging environments.
- ✓ **Compact and Lightweight:** With dimensions of 135 mm × 15.6 mm × 13 mm and a weight of just 16 grams, it is engineered for seamless integration into space-constrained devices.
- ✓ **Omni-Directional Radiation:** Linear polarization and an omni-directional radiation pattern provide consistent performance across diverse orientations.
- ✓ **Flexible Connectivity:** Compatible with FAKRA, TNC, and N-Type connectors, offering versatility for various installation scenarios.
- ✓ **Durable Design:** Constructed from PC + ABS materials, it operates reliably in temperatures ranging from -40 °C to +85 °C and complies with RoHS standards.

- **Performance Highlights**

- ✓ Low VSWR and high return loss minimize signal reflection, optimizing power transfer.
- ✓ High peak gain ensures strong signal reception, while tested radiation patterns confirm stability in both free-space and on-EVB conditions (straight or bent configurations).

- **Target Applications**

- ✓ Ideal for portable GNSS devices, the YEGT001W1AM combines precision, durability, and adaptability. Its modular packaging (up to 320 units per carton) streamlines logistics for large-scale deployments.

Quectel provides comprehensive antenna design support such as simulation, testing and manufacturing for custom antenna solutions to meet your specific application needs. We have regional R & D centers to offer quick response to meet your requirements. Please contact our sales & FAEs if you have any requests.

Contents

Overview	1
Contents	2
1 Specification	3
1.1. Electrical.....	3
1.2. Mechanical & Environmental	5
1.3. Supported GNSS Frequency Bands.....	6
2 Drawing	8
3 Detailed Performance	9
3.1. S-Parameter Test	9
3.1.1. VSWR	9
3.1.2. Return Loss.....	10
3.2. Radiation Performance Test.....	11
3.2.1. Efficiency.....	11
3.2.2. Average Gain	12
3.2.3. Peak Gain	13
3.2.4. 3D & 2D Radiation Pattern	14
3.2.4.1. Test Condition: Free Space Straight	14
3.2.4.2. Test Condition: Free Space Bent	16
3.2.4.3. Test Condition: On 130 mm × 70 mm EVB Straight.....	18
3.2.4.4. Test Condition: On 130 mm × 70 mm EVB Bent.....	20
4 Packaging	22
Contact Us	24
Legal Notices	25
Revision History	27

1 Specification

Test Condition: Free Space & 130 mm × 70 mm EVB

1.1. Electrical

Electrical	
Frequency Range	1559–1606 MHz
Impedance	50 Ω
Polarization	Linear
Radiation Pattern	Omni-directional

Frequency (MHz)	Band	GPS L5	GALILEO	GPS L2	GLONASS	BDS B3	BDS B1I	GPS L1	GLONASS
		E5a	E5b	QZSS L2C	G2			E1	G1
		BDS B2a- B2I	BDS B2b					BDS B1C	
		QZSS L5						QZSS L1	
		IRNSS L5							
		1176	1207	1227	1248	1268	1561	1575	1602
VSWR	FS Straight	-	-	-	-	-	1.2	1.1	1.2
	FS Bent	-	-	-	-	-	1.2	1.1	1.2
	EVB Straight	-	-	-	-	-	1.2	1.2	1.2
	EVB Bent	-	-	-	-	-	1.4	1.4	1.3
Return Loss (dB)	FS Straight	-	-	-	-	-	-21.5	-23.5	-19.6
	FS Bent	-	-	-	-	-	-19.7	-23.1	-20.4

	EVB Straight	-	-	-	-	-	-20.4	-20.2	-22.5
	EVB Bent	-	-	-	-	-	-14.7	-14.9	-16.8
Efficiency (%)	FS Straight	-	-	-	-	-	77.5	75.9	75.1
	FS Bent	-	-	-	-	-	76.2	75.3	70.4
	EVB Straight	-	-	-	-	-	74.9	74.0	71.6
	EVB Bent	-	-	-	-	-	71.2	69.5	69.9
AVG Gain (dB)	FS Straight	-	-	-	-	-	-1.1	-1.2	-1.2
	FS Bent	-	-	-	-	-	-1.2	-1.2	-1.5
	EVB Straight	-	-	-	-	-	-1.3	-1.3	-1.5
	EVB Bent	-	-	-	-	-	-1.5	-1.6	-1.6
Peak Gain (dBi)	FS Straight	-	-	-	-	-	2.9	2.7	2.5
	FS Bent	-	-	-	-	-	2.2	2.1	2.0
	EVB Straight	-	-	-	-	-	3.0	2.9	2.5
	EVB Bent	-	-	-	-	-	1.3	1.1	1.3
VSWR	FS Straight						≤ 1.3		
	FS Bent						≤ 1.2		
	EVB Straight						≤ 1.2		
	EVB Bent						≤ 1.5		
Return Loss	FS Straight						≤ -18.8 dB		
	FS Bent						≤ -19.1 dB		
	EVB Straight						≤ -20.1 dB		
	EVB Bent						≤ -14.7 dB		
Peak Gain	FS Straight						≤ 2.9 dBi		

	FS Bent	≤ 2.4 dBi
	EVB Straight	≤ 3.0 dBi
	EVB Bent	≤ 1.4 dBi

- **Straight:** The connector is vertical.
- **Bent:** The connector is bend.
- **FS:** On Free Space.
- **EVB:** On 130 mm × 70 mm EVB.

1.2. Mechanical & Environmental

Mechanical	
Antenna Dimensions	135 mm × 15.6 mm × 13 mm
Material & Color	PC + ABS & Black
Connector Type	SMA Male
Mounting Type	Terminal
Weight	Typ. 16 g
Environmental	
Operation Temperature	-40 °C to +85 °C
Storage Temperature	-40 °C to +85 °C
RoHS Compliant	Yes


1.3. Supported GNSS Frequency Bands

GNSS Frequency Bands (MHz)					
GPS	L1 Centre 1575.42 (1565–1586)	L2 Centre 1227.6 (1217–1238)	L5 Centre 1176.45 (1164–1189)		
	√	-	-		
GLONASS	G1-L10C-L10F Centre 1601 (1595–1606)	G2-L20C-L20F Centre 1248.06 (1241–1255)	G3-L30C Centre 1202.025 (1189–1213)		
	√	-	-		
GALILEO	E1 Centre 1575.42 (1563–1588)	E5a Centre 1176.45 (1166–1187)	E5b Centre 1207.14 (1197–1218)	E6 Centre 1278.75 (1258–1300)	
	√	-	-	-	
BDS	B1I Centre 1561.098 (1559–1564)	B1C (BDS-3) Centre 1575.42 (1559–1592)	B2a-B2I Centre 1176.45 (1166–1187)	B2b Centre 1207.14 (1197–1217)	B3 Centre 1268.52 (1258–1279)
	√	√	-	-	-
QZSS	L1 Centre 1575.42 (1573–1578)	L2C Centre 1227.6 (1226–1229)	L5 Centre 1176.45 (1166–1187)	L6 Centre 1278.75 (1257–1300)	
	√	-	-	-	
IRNSS	L5 Centre 1176.45 (1164–1189)				
	-				

GNSS Bands and Constellations



2 Drawing




UNIT:mm

Note: If you use a torque wrench, the recommended force for mounting the antenna is 0.9Nm and the maximum torque to prevent antenna damage is 1.17Nm.

3 Detailed Performance

3.1. S-Parameter Test


3.1.1. VSWR



VSWR

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
FS Straight	-	-	-	-	-	1.2	1.1	1.2
FS Bent	-	-	-	-	-	1.2	1.1	1.2
EVB Straight	-	-	-	-	-	1.2	1.2	1.2
EVB Bent	-	-	-	-	-	1.4	1.4	1.3

3.1.2. Return Loss




Return Loss (dB)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
FS Straight	-	-	-	-	-	-21.5	-23.5	-19.6
FS Bent	-	-	-	-	-	-19.7	-23.1	-20.4
EVB Straight	-	-	-	-	-	-20.4	-20.2	-22.5
EVB Bent	-	-	-	-	-	-14.7	-14.9	-16.8

3.2. Radiation Performance Test


3.2.1. Efficiency



Efficiency (%)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
FS Straight	-	-	-	-	-	77.5	75.9	75.1
FS Bent	-	-	-	-	-	76.2	75.3	70.4
EVB Straight	-	-	-	-	-	74.9	74.0	71.6
EVB Bent	-	-	-	-	-	71.2	69.5	69.9


3.2.2. Average Gain



Average Gain (dB)

Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
FS Straight	-	-	-	-	-	-1.1	-1.2	-1.2
FS Bent	-	-	-	-	-	-1.2	-1.2	-1.5
EVB Straight	-	-	-	-	-	-1.3	-1.3	-1.5
EVB Bent	-	-	-	-	-	-1.5	-1.6	-1.6

3.2.3. Peak Gain




Peak Gain (dBi)


Frequency (MHz)	1176	1207	1227	1248	1268	1561	1575	1602
FS Straight	-	-	-	-	-	2.9	2.7	2.5
FS Bent	-	-	-	-	-	2.2	2.1	2.0
EVB Straight	-	-	-	-	-	3.0	2.9	2.5
EVB Bent	-	-	-	-	-	1.3	1.1	1.3

3.2.4. 3D & 2D Radiation Pattern

3.2.4.1. Test Condition: Free Space Straight


- Test Chamber: FS-S-1






3.2.4.2. Test Condition: Free Space Bent


- Test Chamber: FS-S-1






3.2.4.3. Test Condition: On 130 mm × 70 mm EVB Straight


- Test Chamber: FS-S-1










3.2.4.4. Test Condition: On 130 mm × 70 mm EVB Bent


- Test Chamber: FS-S-1





4 Packaging

Step	Packaging Picture / 2D Picture	Description
1		<p>10 antenna products in a one-piece bag. (10 Antennas / One-piece Bag)</p>
2		<p>40 antenna products in a PE bag. (40 Antennas / PE Bag)</p>
3		<p>(18 PE Bags / Carton Box) (720 Antennas / Carton Box) Estimated quantity Products that cannot fill the entire carton box are packed in a suitable size carton box. <u>Carton Size:</u> <u>L × W × H = 370 × 370 × 295 mm</u></p>
4		<p>Position for Attaching Labels</p> <ul style="list-style-type: none"> ① Carton Label ② Quality Label

5		Sealing Cartons H-shaped sealing cartons
Note	The initial packaging method described above is for reference only, and the final actual packaging method shall be subject to the actual shipping packaging.	

Contact Us

At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

Quectel Wireless Solutions Co., Ltd.

No. 8 Waipojing Road, Sijing Town, Songjiang District, Shanghai 201601, China

Tel: +86 21 5108 6236

Email: info@quectel.com

Or our local offices. For more information, please visit:

<https://www.quectel.com/contact/>.

For technical support, or to report documentation errors, please visit:

<https://www.quectel.com/tech-support/>.

Or email us at: support@quectel.com.

Legal Notices

We provide this document to support your product design. You are required to design your products based on the specifications and parameters set forth herein. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an “as available” basis. You acknowledge and agree that we may add to, amend, or restate this document at any time at our sole discretion without any prior notice to you, and such additions, amendments, or restatements shall be binding upon you.

Use and Disclosure Restrictions

License Agreements

The recipient of any hardware, software, materials, or documentation provided by us shall keep such content confidential, unless expressly authorized by us. The recipient shall not disclose, access, or use any part of the received content for any purpose other than the execution and implementation of the intended project.

Copyright

Our and third-party products hereunder may contain copyrighted materials, including but not limited to protected content, hardware, software, and documentation owned by us or applicable third parties. Unless prior written consent is obtained, you shall not access, use, or disclose any documents or information provided by us, nor shall you copy, reproduce, republish, display, translate, distribute, merge, modify, or create derivative works from any such copyrighted materials. We and the applicable third party retain exclusive rights to all copyrighted materials. No license to any patents, copyrights, trademarks, or service marks shall be granted or transferred. For the avoidance of doubt, no form of purchase shall be construed as granting any license beyond a normal, non-exclusive, royalty-free license to use the product. We reserve the right to pursue legal action against any violation of confidentiality obligations, unauthorized use, or any other unlawful or malicious use of the aforementioned documents and information.

Trademarks

Unless otherwise expressly provided, nothing in this document shall be construed as conferring any rights to use any trademark, trade name, name, abbreviation, or counterfeit thereof owned by us or any third party in advertising, publicity, or any other contexts.

Third-Party Rights

You understand that this document may refer to hardware, software, and/or documentation owned by one or more third parties (“third-party materials”). Use of such third-party materials is subject to all applicable restrictions and obligations set forth herein.

We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise maintain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing, course of performance, or usage of trade.

Privacy Policy

To enable product functionality, certain device data may be uploaded to our or third-party servers, including those operated by carriers, chipset suppliers, or servers designated by you. We strictly comply with applicable laws and regulations and will retain, use, disclose, or otherwise process relevant data solely for the purpose of enabling product functionality, or as permitted by applicable laws. Before interacting with any third party regarding data exchange, please be informed of and understand their privacy and data security policies.

Disclaimer

- a) We shall not be liable for any damages resulting from failure to comply with applicable operational or design specifications.
- b) We shall bear no liability for any inaccuracies or omissions in this document, nor for any damages arising from the use of the information contained herein.
- c) While we make every effort to ensure the integrity, accuracy, and timeliness of the features and functions under development, errors or omissions may nevertheless occur. Unless otherwise provided in a valid written agreement, we make no warranties of any kind, express, implied, or statutory, and disclaim all liability for any loss or damage arising from the use of any features or functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage is foreseeable.
- d) We assume no legal responsibility for the accessibility, safety, accuracy, availability, legality, or completeness of any information, content, advertising, commercial offers, products, services, or materials on third-party websites or third-party resources.

Copyright © Quectel Wireless Solutions Co., Ltd. 2026. All rights reserved.

Revision History

Version	Date	Author	Note
-	2024-05-24	Mordecai Liu/ Lance Sun/ David Liu/ Rainey Liao	Creation of the document
1.0	2024-05-24	Mordecai Liu/ Lance Sun/ David Liu/ Rainey Liao	First official release
1.1	2024-09-03	Mordecai Liu	Numerous changes were made to this document. It should be read in its entirety.
1.2	2024-11-07	Lance Sun	Updated the drawing (Chapter 2).
1.3	2025-06-12	Rainey Liao	1. Updated the antenna image (Cover page). 2. Updated the overview.
1.4	2026-01-12	Strong Qiang	Updated the packaging (Chapter 4).

QUECTEL

www.quectel.com