

# Antenna YDX001AA Datasheet

#### **Antenna Services**

Version: 2.1

Date: 2022-10-17

Status: Released





At Quectel, our aim is to provide timely and comprehensive services to our customers. If you require any assistance, please contact our headquarters:

#### Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236 Email: <u>info@quectel.com</u>

#### Or our local offices. For more information, please visit:

http://www.quectel.com/support/sales.htm.

#### For technical support, or to report documentation errors, please visit:

http://www.quectel.com/support/technical.htm.

Or email us at: support@quectel.com.

# **Legal Notices**

We offer information as a service to you. The provided information is based on your requirements and we make every effort to ensure its quality. You agree that you are responsible for using independent analysis and evaluation in designing intended products, and we provide reference designs for illustrative purposes only. Before using any hardware, software or service guided by this document, please read this notice carefully. Even though we employ commercially reasonable efforts to provide the best possible experience, you hereby acknowledge and agree that this document and related services hereunder are provided to you on an "as available" basis. We may revise or restate this document from time to time at our sole discretion without any prior notice to you.

# **Use and Disclosure Restrictions**

## **License Agreements**

Documents and information provided by us shall be kept confidential, unless specific permission is granted. They shall not be accessed or used for any purpose except as expressly provided herein.

# Copyright

Our and third-party products hereunder may contain copyrighted material. Such copyrighted material shall not be copied, reproduced, distributed, merged, published, translated, or modified without prior written consent. We and the third party have exclusive rights over copyrighted material. No license shall be granted or conveyed under any patents, copyrights, trademarks, or service mark rights. To avoid ambiguities, purchasing in any form cannot be deemed as granting a license other than the normal non-exclusive, royalty-free license to use the material. We reserve the right to take legal action for noncompliance with abovementioned requirements, unauthorized use, or other illegal or malicious use of the material.

Antenna\_Datasheet 1 / 15



#### **Trademarks**

Except as otherwise set forth herein, nothing in this document shall be construed as conferring any rights to use any trademark, trade name or name, abbreviation, or counterfeit product thereof owned by Quectel or any third party in advertising, publicity, or other aspects.

#### **Third-Party Rights**

This document may refer to hardware, software and/or documentation owned by one or more third parties ("third-party materials"). Use of such third-party materials shall be governed by all restrictions and obligations applicable thereto.

We make no warranty or representation, either express or implied, regarding the third-party materials, including but not limited to any implied or statutory, warranties of merchantability or fitness for a particular purpose, quiet enjoyment, system integration, information accuracy, and non-infringement of any third-party intellectual property rights with regard to the licensed technology or use thereof. Nothing herein constitutes a representation or warranty by us to either develop, enhance, modify, distribute, market, sell, offer for sale, or otherwise maintain production of any our products or any other hardware, software, device, tool, information, or product. We moreover disclaim any and all warranties arising from the course of dealing or usage of trade.

# **Privacy Policy**

To implement module functionality, certain device data are uploaded to Quectel's or third-party's servers, including carriers, chipset suppliers or customer-designated servers. Quectel, strictly abiding by the relevant laws and regulations, shall retain, use, disclose or otherwise process relevant data for the purpose of performing the service only or as permitted by applicable laws. Before data interaction with third parties, please be informed of their privacy and data security policy.

## **Disclaimer**

- a) We acknowledge no liability for any injury or damage arising from the reliance upon the information.
- b) We shall bear no liability resulting from any inaccuracies or omissions, or from the use of the information contained herein.
- c) While we have made every effort to ensure that the functions and features under development are free from errors, it is possible that they could contain errors, inaccuracies, and omissions. Unless otherwise provided by valid agreement, we make no warranties of any kind, either implied or express, and exclude all liability for any loss or damage suffered in connection with the use of features and functions under development, to the maximum extent permitted by law, regardless of whether such loss or damage may have been foreseeable.
- d) We are not responsible for the accessibility, safety, accuracy, availability, legality, or completeness of information, advertising, commercial offers, products, services, and materials on third-party websites and third-party resources.

Copyright © Quectel Wireless Solutions Co., Ltd. 2022. All rights reserved.

Antenna\_Datasheet 2 / 15



# **About the Document**

# **Revision History**

Version	Date	Author	Note					
1.0	2020-09-10	Kenny YIN	Initial					
1.1	2020-12-11	Kenny YIN	Updated the antenna image in Chapter 2.					
1.2	2021-01-27	Kenny YIN	Added IP rating description.					
1.3	2021-07-25	Kenny YIN	<ol> <li>1. Updated working temperature. (Chapter 3)</li> <li>2. Added detailed passive electrical specifications. (Chapter 3)</li> </ol>					
1.4	2021-12-01	Kenny YIN	Updated the product description in Chapter 1.					
2.0	2022-03-10	Vinnie LIU	Updated the RF data (Chapter 4).					
2.1	2022-10-17	Aria CHU	Deleted the IP rating.					

Antenna\_Datasheet 3 / 15



#### **Contents**

Ab	out the Doci	ument	
Со	ntents		4
1	Product De	escription	5
2	Product Fe	eatures	5
3	Duaduat Co	pecifications	
3	Product Sp	Decifications	
4	Overall Pe	rformance	7
	4.1. Test	Environment	7
	4.2. VSW	/R	8
	4.3. Effic	iency	g
	4.4. Gain	1	10
	4.5. Radi	iation Pattern	11
	4.5.1.	824 MHz	12
	4.5.2.	954 MHz	
	4.5.3.	1754 MHz	13
	4.5.4.	2304 MHz	
	4.5.5.	2690 MHz	14
5	Product Si	76	15



# 1 Product Description

This Quectel external 4G antenna covers main 4G LTE bands and is compatible with 3G/2G/LPWA bands as well. The external antenna is barely influenced by the internal environment of devices, giving a much better performance in efficiency, radiation and gain whilst providing an optimized solution for a customer product. Quectel also offers flexible installation with custom cable length and connector options.

#### 2 Product Features

- Cellular LTE
- High efficiency
- Excellent performance



Antenna\_Datasheet 5 / 15



# 3 Product Specifications

Passive Elec	trical Spe	ecifications	;									
Frequency Ra	ange			824–27	824–2700 MHz							
Input Impende	ence			50 Ω	50 Ω							
VSWR				≤ 6.0	≤ 6.0							
Gain	Gain :											
Polarization T	уре			Linear								
Detailed Pass	ive Elect	rical Speci	fications									
Frequency Range (MHz)	698–960	1176–1280	1400–1610	1710–2170	2170–2690	3300–4000	4000–5000	5000–6000				
VSWR (Max.)	5.5	-	-	3.2	2.6	-	-	-				
Average Efficiency (%)	61.8	-	-	52.4	83.3	-	-	-				
Max. Peak Gain (dBi)	1.5	-	-	2.02	2.22	-	-	-				
Mechanical S	Specificat	tions										
Antenna Size				208 m	208 mm × Φ 12 mm							
Casing				PC + /	PC + ABS							
Connector Typ		Male (Cente	r Pin)									
Working Temp	ng Temperature -40 °C to +85 °C											
Radome Colo	r			Black	Black							

Antenna\_Datasheet 6 / 15



## 4 Overall Performance

#### 4.1. Test Environment


- KEYSIGHT ENA Network Analyzer E5063A 100 kHz 8.5 GHz.
- RayZone®2800 Chamber 5G (FR1) SISO/MIMO, 600 MHz 8.5 GHz.



Antenna\_Datasheet 7 / 15



#### 4.2. **VSWR**





Frequency (MHz)	824	894	960	1710	1880	2170	2500	2690
VSWR	5.52	1.65	1.86	2.92	3.17	2.58	1.71	2.09

Antenna\_Datasheet 8 / 15



# 4.3. Efficiency







Frequency (MHz)	824	894	964	1714	1884	2174	2504	2690
Efficiency (%)	28.19	70.17	72.93	47.18	44.24	63.99	91.31	83.31

Antenna\_Datasheet 9 / 15



#### 4.4. Gain






Frequency (MHz)	824	894	964	1714	1884	2174	2504	2690
Gain (dBi)	-2.63	1.04	0.68	2.02	0.37	0.09	2.13	1.67

Antenna\_Datasheet 10 / 15



#### 4.5. Radiation Pattern


• Test condition: free space.




Antenna\_Datasheet 11 / 15



#### 4.5.1. 824 MHz




#### 4.5.2. 954 MHz




Antenna\_Datasheet 12 / 15






#### 4.5.3. 1754 MHz




Antenna\_Datasheet 13 / 15



#### 4.5.4. 2304 MHz




## 4.5.5. 2690 MHz




Antenna\_Datasheet 14 / 15





# **5 Product Size**



Antenna\_Datasheet 15 / 15